



RMM1

Remote Monitoring Module



Applications

The RMM1 can be used with two HLD7 or HLD9 drivers in standalone configuration or two HLD7's or two HLD9's in a phased array configuration.

The device monitors a number of events that can activate the automatic e-mail alert system including:

- › Loop wire disconnect
- › Driver power failure
- › Communication failure
- › Overtemperature

Components

- › Remote Monitoring Module
- › HLD connection cable (x2)
- › Network cable
- › Power supply (Micro USB)

PRODUCT INFORMATION

The RMM1 is an accessory for the HLD7 and HLD9 large area hearing loop drivers. It can adjust both drive level and loop output levels via an embedded web service. This can be done from a desktop or mobile device without the need to return to the driver(s), reducing installation time.

The RMM1 allows the hearing loop driver(s) to self-monitor and send an email alert if a fault arises, such as a loop wire disconnect, driver power failure or general output stage failure.

Physical Data

Dimensions	Height – 1.57" Width – 4.60" Length – 4.50"
Weight	1.01 lbs
Construction	ABS Plastic Construction Housing
Finish	Matt Black Fine Texture

Technical Data

Inputs	DC Power	Micro USB
	Network Comms	RJ45 Connector
	HLD Comms	RJ11 Connector
Display	Power/Network	LED Indicators
	HLD Comms	



contacta 

Phone: (616) 392-3400
Email: sales@contactainc.com
www.contactainc.com