

RF-RX1

Portable Radio Frequency Receiver



CONTACTA RADIO FREQUENCY

The Contacta Portable RF Receiver provides high-quality sound from Contacta transmitters and transceivers. It has a signal range up to 492ft with no limit to the number of receivers that can be used with the system. The Receiver can be charged with the 2 Bay Charging Station (RF-RX-CS2) or the 20 Bay Charging Case (RF-DC20).

Physical Data

Dimensions	Height – 3.34" Width – 1.96" Depth – 0.59"
Weight	0.14lbs
Finish	Grey

Technical Data

Power Supply	Lithium ion rechargeable battery 3.7V/1100mAh
Battery Life	Approximately 20 hours
Transmission Frequency	2.4GHz (ISM band)
Modulation	FSK, with hopping
Transmission Range	492ft in open air/262ft in buildings
Channels	40 channels
Frequency Response	50Hz - 7kHz
Transmission Power	10mW
Sensitivity	-95dBm
Data Rate	2Mbps
Connectors	2 x 3.5mm 4 contact socket / Micro USB charge port



Applications

- › Conference and Meeting Rooms
- › Court Buildings
- › Lecture Halls, Schools, and Universities
- › Cinemas and Theatres
- › Places of Worship
- › Museums

Includes

- › Belt clip
- › Earbuds
- › Lanyard
- › Micro USB Power Supply

contacta

Phone: (616) 392-3400
Email: sales@contactainc.com
www.contactainc.com