

RF-TX1

Portable Radio Frequency Transmitter



CONTACTA RADIO FREQUENCY

The Contacta Portable RF Transmitter is lightweight and gives on-the-move transmission of clear speech to Contacta's range of portable receivers across 40 channels. The Transmitter is supplied with a belt-clip which allows users to unobtrusively wear the device when needed. A micro USB power supply makes charging simple and fast.

Physical Data

Dimensions	Height – 3.34" Width – 1.96" Depth – 0.59"
Weight	0.14lbs
Finish	Grey

Technical Data

Power Supply	Lithium ion rechargeable battery 3.7V/1100mAh
Battery Life	Approximately 12 hours
Transmission Frequency	2.4GHz (ISM band)
Modulation	FSK, with hopping
Transmission Range	492ft in open air/262ft in buildings
Channels	40 channels
Frequency Response	50Hz - 7kHz
Transmission Power	10mW
Sensitivity	-95dBm
Data Rate	2Mbps
Connectors	2 x 3.5mm 4 contact socket/Micro USB charge port



Applications

- › Conference and Meeting Rooms
- › Court Buildings
- › Lecture Halls, Schools, and Universities
- › Cinemas and Theatres
- › Places of Worship
- › Museums

Includes

- › Belt clip
- › Earworn microphone (RF-TRX-MCB)
- › Lanyard
- › Micro USB Power Supply

contacta

Phone: (616) 392-3400
Email: sales@contactainc.com
www.contactainc.com